

RIGOL DOST

# DG5000 series Waveform Generators

DG5000 is a multifunctional generator that combines many functions in one, including Function Generator, Arbitrary Waveform Generator, IQ Baseband Source/IQ IF Source, Frequency Hopping Source (optional) and Pattern Generator (optional). It provides single and dual-channel models. The dual-channel model, with two channels having complete equivalent functions and precisely adjustable phase deviation between the two channels, is a real dual-channel signal generator.

DG5000, adopting the Direct Digital Synthesizer (DDS) technology, can provide stable, precise, pure and low distortion signal. The user-friendly interface design and panel layout bring users exceptional experience. Besides, the remote control of the generator can be easily done through different standard configuration interfaces, which provides more solutions for users.

### **DG5000 series Waveform Generators**





#### Features and Benefits

- 4.3 inches, 16M true color TFT LCD.
- 350 MHz, 250 MHz or 100 MHz maximum sine output frequency, 1 GSa/s sample rate, 14 bits resolution.
- Single/dual-channel models. The dual-channel model supports frequency and phase coupling.
- The 16+2 channels digital output module (optional) together with the analog channel can rebuild the more mixed signals in daily practice.
- Support an external power amplifier (optional) that can be configured online.
- · Support frequency hopping (optional) with hopping interval up to 80 ns and arbitrary editing frequency hopping patterns.
- 14 standard waveform functions: Sine, Square, Ramp, Pulse, Noise, Sinc, Exponential Rise, Exponential Fall, ECG, Gauss, Haversine, Lorentz, Dual Tones and DC.
- Rise/Fall Time of the Pulse could be adjusted separately.
- · Enable to edit arbitrary waveform up to 512 kpts and output arbitrary waveforms up to 128 Mpts.
- Support AM, FM, PM, ASK, FSK, PSK and PWM modulations.
- · Support user-defined IQ vector signal modulation and IQ baseband/IF source output.
- Support Frequency Sweep and Burst output.
- Abundant I/O: waveform output, synchronous signal output, modulation input, 10 MHz clock input/output, trigger input/output.
- Enable to store and recall waveform data and instrument state, and support versatile file types. Standard configuration with 1 GBytes flash memory.
- Plenty of standard interfaces: double USB Hosts, USB Device, LAN, and GPIB (IEEE-488.2).
- · Seamlessly interconnected with RIGOL USB-TMC digital oscilloscopes for loading and reappearing waveforms.
- Support USB flash device storage for FAT files.
- Support PictBridge printer.
- Provide security lock hole.
- Support remote control through 10/100M Ethernet web.
- · Conform to LXI-C instrument standards (Version 1.2).
- Provide Chinese and English built-in help and input methods.
- · Provide powerful waveform editing PC software.

## **Advanced functions**

	CH1		CH2	
Rate 1.000,000 Mbps Pat PN23 IQ Map 64QAM Data IQ Map Cos Add Qut		Freq Ampl Offset Phase	Ampl 0.0 mdBm Offset 0.000,0 V <sub>DC</sub>	
мар	*Cos			r
	•☆ <sup></sup> <b>H1:</b> HighZ @1X	Mod C	<b>H2:</b> 50 Ω 1	×

IQ Modulation

RIGOL				5			
	CH1				CH2		
FH Map Switch DispType StartPt Interval	Map3 OFF Chess 1 10.000.00	0.0 ms	SN4095	4093	4085	4054	FH
HopNum	4095		apN 1	2 3	4 5	6 7 8	
Freq Hop	CH1: Hi	ghZ 1X	C	:H2:	50 Ω	1X	
Switch Off	Interval	Start DispPt	DispTy Chess		oad ⁄lap	Edit Map	

**Frequency Hopping** 



IQ Mapping Selection



IQ Mapping Edit



AM



FSK



PWM



Burst

RIG	OL			•	<	
		CH1			CH2	
Sweep	100	0.0 ms		Freq	350.000,00	0,000 MHz
Return	0.0	ms		Ampl	0.0 mdBm	
Start	10.000,000 Hz		Offset	0.000,0 Vpc		
End	250	0.000,000,0	000 MHz	Phase	0.00 °	
Mark	OFF	=				
EHold	1.0	00,0 s	$\wedge$	,		1
Swee	эp	CH1: Hig	ghZ 🐠1X :	Sweep C	H2: 50 Ω	1X
SwpT	ype	SwpTime	Return	Start	End	Source
Line	ar 🖕		Time	Center	Span	



Sweep

ARB

#### Specification

All the specifications can be guaranteed if the following two conditions are met unless where noted. • The generator is within the calibration and has performed self-calibration. • The generator has been working continuously for 30 minutes at specified temperature (18°C ~ 28°C).

All the specifications are guaranteed unless those marked with "typical".

Model	DG5352	DG5351	DG5252	DG5251	DG5102	DG5101	
Channel	2	1	2	1	2	1	
Maximum Frequency	350	350 MHz 250 MHz 100 MHz				/Hz	
Sample Rate		1 GSa/s					
Waveforms							
Standard Waveforms	Sine, Square, Ramp, Pulse, Noise						
Arbitrary Waveforms	Sinc, Exponential Rise, Exponential Fall, ECG, Gauss, HaverSine, Lorentz, Dual-Tone, DC						

Frequency Characteristics			
Sine	1 µHz to 350 MHz	1 µHz to 250 MHz	1 µHz to 100 MHz
Square	1 µHz to 120 MHz	1 µHz to 120 MHz	1 µHz to 100 MHz
Ramp	1 µHz to 5 MHz	1 µHz to 5 MHz	1 µHz to 3 MHz
Pulse	1 µHz to 50 MHz	1 µHz to 50 MHz	1 µHz to 50 MHz
Noise	250 MHz Bandwidth	250 MHz Bandwidth	100 MHz Bandwidth
Arb	1 µHz to 50 MHz	1 µHz to 50 MHz	1 µHz to 50 MHz
Resolution	1 µHz		
Accuracy	±1 ppm, 18 °C to 28 °C		

Sine Wave Spectrum Purity	<i>,</i>		
Harmonic Distortion	Typical (0 dBm)	Typical (0 dBm)	Typical (0 dBm)
	≤100MHz: <-45dBc	≤100MHz: <-45dBc	≤100MHz: <-45dBc
	>100MHz: <-35dBc	>100MHz: <-35dBc	
<b>Total Harmonic Distortion</b>	<0.5% (10 Hz to 20 kHz, 0 dBm)		
Spurious (non-harmonic)	Typical (0 dBm)	Typical (0 dBm)	Typical (0 dBm)
	≤100MHz: <-50dBc	≤100MHz: <-50dBc	≤100MHz: <-50dBc
	>100MHz: -50dBc+6dBc/octave	>100MHz: -50dBc+6dBc/octave	
Phase Noise	Typical (0 dBm, 10 kHz deviation)		
	10 MHz: <-110 dBc		

Signal Characteristics			
Square			
Rise/Fall Time	Typical Value (1Vpp)	Typical Value (1Vpp)	Typical Value (1Vpp)
	< 2.5 ns	< 2.5 ns	< 3 ns
Overshoot	Typical Value (1Vpp)	2.0.10	
	< 5%		
Duty Cycle	≤ 10 MHz: 20.0% to 80.0%		
	10 MHz to 40 MHz: 40.0% to 60.	0%	
	> 40 MHz: 50.0% (fixed)		
Non-symmetry	1% of period + 5 ns		
Jitter (rms)	Typical Value (1Vpp)		
	≤ 30 MHz: 10ppm+500 ps		
	> 30 MHz: 500 ps		

Ramp	
Linearity	≤ 0.5% of peak output
Symmetry	0% to 100%
Pulse	
Period	20 ns to 1000000 s
Pulse Width	4 ns to 1000000 s
Leading/Trailing Edge Time	2.5 ns to 1 ms (could be adjusted separately)
Overshoot	<5%
Jitter (rms)	Typical Value (1Vpp)
	10 ppm+500 ps

Arb	
Waveform Length	2 to 128M points
Vertical Resolution	14 bits
Mode	Normal Mode, Play Mode
Sample Rate	Normal Mode (Waveform Length is from 2 to 16M points): 1G Sa/s (fixed)
	Play Mode (Waveform Length is from 16k to 128M points): ≤1G Sa/s (variable)
Minimum Rise/Fall Time	Typical Value (1Vpp)
	≤3 ns
Jitter (rms)	3 ns
Interpolation Method	Close, Linear, Spline
Edit Method	Edit Point, Edit Block
Non-Volatile Memory	1G Bytes

Output Characteristi	cs		
Amplitude (into 50 C	2)		
Range	≤ 100 MHz: 5 mVpp to 10 Vpp	≤100MHz: 5mVpp to 10Vpp	5mVpp to 10Vpp
	≤ 300 MHz: 5 mVpp to 5 Vpp	≤250MHz: 5mVpp to 5Vpp	
	≤ 350 MHz: 5 mVpp to 2 Vpp		
Accuracy	Typical (1 kHz Sine, 0 V Deviation, >1	0 mVpp, Auto)	
	± 1% of setting ± 1 mVpp		
Flatness	Typical (Sine, 1.25 Vpp, 50 Ω)	Typical (Sine, 1.25 Vpp, 50 Ω)	Typical (Sine, 1.25 Vpp, 50 Ω)
	< 10 MHz: ± 0. 1dB	< 10 MHz: ±0.1dB	< 10 MHz: ± 0.1 dB
	10 MHz to 60 MHz: ±0.2 dB	10 MHz to 6 0MHz: ±0.2 dB	10 MHz to 60 MHz: ± 0.2 dB
	60 MHz to 100 MHz: ±0.4 dB	60 MHz to 100 MHz: ±0.4 dB	60 MHz to 100 MHz: ± 0.4 dB
	100 MHz to 250 MHz: ±1.0 dB	100 MHz to 250 MHz: ±1.0 dB	
	>250 MHz: ±1.5 dB		
Units	Vpp, Vrms, dBm, High Level, Low Lev	vel	
Resolution	0.1 mV or 4 digits		

Offset (into 50 Ω)	
Range	±5 Vpk ac + dc
Accuracy	1% of setting + 5mV + 0.5% of amplitude
Waveform Output	
Impedance	$50 \Omega$ (typical)
Isolation	42 Vpk max. to Earth
Protection	Over-temperature protected, Short-circuit protected, Overload relay automatically disables main output

FH Characteristic	
FH Bandwidth	100 kHz to 250 MHz
FH Rate	1 Hop/s to 12.5M Hop/s
Frequency Point Numbers	4096
Sequence Length	4096

Modulation Characteristics	
Modulation Types	AM、FM、PM、ASK、FSK、PSK、PWM、IQ

AM				
Carrier Waveforms	Sine, Square, Ramp, Arb (except DC)			
Source	Internal/External			
Modulating Waveforms	Sine, Square, Ramp, Noise, Arb (2 mHz to 50 kHz)			
Depth	0% to 120%			
- • [				
FM				
Carrier Waveforms	Sine, Square, Ramp, Arb (except DC)			
Source	Internal/External			
Modulating Waveforms	Sine, Square, Ramp, Noise, Arb (2 mHz to 50 kHz)			
<u> </u>				
PM				
Carrier Waveforms	Sine, Square, Ramp, Arb (except DC)			
Source	Internal/External			
Modulating Waveforms	Sine, Square, Ramp, Noise, Arb (2 mHz to 50 kHz)			
Phase Deviation	0° to 360°			
ASK				
Carrier Waveforms	Sine, Square, Ramp, Arb (except DC)			
Source	Internal/External			
Modulating Waveforms	Square with 50% duty cycle (2 mHz to 1 MHz)			
FSK				
-	Sing Source Down Ark (avent DC)			
Carrier Waveforms	Sine, Square, Ramp, Arb (except DC)			
Source	Internal/External			
Modulating Waveforms	Square with 50% duty cycle (2 mHz to 1 MHz)			
PSK				
Carrier Waveforms	Sine, Square, Ramp, Arb (except DC)			
Source	Internal/External			
Modulating Waveforms	Square with 50% duty cycle (2 mHz to 1 MHz)			
PWM				
Carrier Waveform	Pulse			
Source	Internal/External			
Modulating Waveforms	Sine, Square, Ramp, Noise, Arb (2 mHz to 50 kHz)			
Width Deviation	0% to 100% of Pulse Width			
IQ				
Carrier Waveform	Sine (max. 200 MHz)Sine (max. 200 MHz)Sine (max. 100 MHz)			
	Internal/External			
Source	Internal/External			
Code Pattern	PN Sequence, 4 bits code pattern, User			
Code Pattern	PN Sequence, 4 bits code pattern, User			
Code Pattern IQ Mapping	PN Sequence, 4 bits code pattern, User 4QAM, 8QAM, 16QAM, 32QAM, 64QAM, BPSK, QPSK, OQPSK, 8PSK, 16PSK, User			
Code Pattern IQ Mapping Code Rate	PN Sequence, 4 bits code pattern, User 4QAM, 8QAM, 16QAM, 32QAM, 64QAM, BPSK, QPSK, OQPSK, 8PSK, 16PSK, User			
Code Pattern IQ Mapping Code Rate Burst Characteristics	PN Sequence, 4 bits code pattern, User 4QAM, 8QAM, 16QAM, 32QAM, 64QAM, BPSK, QPSK, OQPSK, 8PSK, 16PSK, User 1 bps to 1 M bps			
Code Pattern IQ Mapping Code Rate Burst Characteristics Carrier Waveforms	PN Sequence, 4 bits code pattern, User 4QAM, 8QAM, 16QAM, 32QAM, 64QAM, BPSK, QPSK, OQPSK, 8PSK, 16PSK, User 1 bps to 1 M bps Sine, Square, Ramp, Pulse, Noise, Arb (except DC)			
Code Pattern IQ Mapping Code Rate Burst Characteristics Carrier Waveforms Carrier Frequency	PN Sequence, 4 bits code pattern, User   4QAM, 8QAM, 16QAM, 32QAM, 64QAM, BPSK, QPSK, OQPSK, 8PSK, 16PSK, User   1 bps to 1 M bps   Sine, Square, Ramp, Pulse, Noise, Arb (except DC)   1 μHz to 120 MHz 1 μHz to 120   1 μHz to 100 MHz			
Code Pattern IQ Mapping Code Rate Burst Characteristics Carrier Waveforms Carrier Frequency Burst Count	PN Sequence, 4 bits code pattern, User   4QAM, 8QAM, 16QAM, 32QAM, 64QAM, BPSK, QPSK, OQPSK, 8PSK, 16PSK, User   1 bps to 1 M bps   Sine, Square, Ramp, Pulse, Noise, Arb (except DC)   1 µHz to 120 MHz 1 µHz to 120 1 µHz to 100 MHz   1 to 1 000 000 or Infinite			
Code Pattern IQ Mapping Code Rate Burst Characteristics Carrier Waveforms Carrier Frequency Burst Count Start/Stop Phase	PN Sequence, 4 bits code pattern, User   4QAM, 8QAM, 16QAM, 32QAM, 64QAM, BPSK, QPSK, OQPSK, 8PSK, 16PSK, User   1 bps to 1 M bps   Sine, Square, Ramp, Pulse, Noise, Arb (except DC)   1 µHz to 120 MHz 1 µHz to 120   1 to 1 000 000 or Infinite   0° to 360°			
Code Pattern IQ Mapping Code Rate Burst Characteristics Carrier Waveforms Carrier Frequency Burst Count Start/Stop Phase Internal Period	PN Sequence, 4 bits code pattern, User 4QAM, 8QAM, 16QAM, 32QAM, 64QAM, BPSK, QPSK, OQPSK, 8PSK, 16PSK, User 1 bps to 1 M bps Sine, Square, Ramp, Pulse, Noise, Arb (except DC) 1 μHz to 120 MHz 1 μHz to 120 1 μHz to 100 MHz 1 to 1 000 000 or Infinite 0° to 360° 1 μs to 500 s			
Code Pattern IQ Mapping Code Rate Burst Characteristics Carrier Waveforms Carrier Frequency Burst Count Start/Stop Phase Internal Period Gated Source	PN Sequence, 4 bits code pattern, User   4QAM, 8QAM, 16QAM, 32QAM, 64QAM, BPSK, QPSK, OQPSK, 8PSK, 16PSK, User   1 bps to 1 M bps   Sine, Square, Ramp, Pulse, Noise, Arb (except DC)   1 µHz to 120 MHz 1 µHz to 120   1 to 1 000 000 or Infinite   0° to 360°   1 µs to 500 s   External Trigger			
Code Pattern IQ Mapping Code Rate Burst Characteristics Carrier Waveforms Carrier Frequency Burst Count Start/Stop Phase Internal Period	PN Sequence, 4 bits code pattern, User 4QAM, 8QAM, 16QAM, 32QAM, 64QAM, BPSK, QPSK, OQPSK, 8PSK, 16PSK, User 1 bps to 1 M bps Sine, Square, Ramp, Pulse, Noise, Arb (except DC) 1 μHz to 120 MHz 1 μHz to 120 1 μHz to 100 MHz 1 to 1 000 000 or Infinite 0° to 360° 1 μs to 500 s			

Sweep Characteristics			
Carrier Waveforms	Sine, Square, Ramp, Arb (except DC)		
Туре	Linear, Log or Step		
Direction	Up or Down		
Start/Stop Frequency		µHz to 250 MHz	1 µHz to 100 MHz
Sweep Time	1 ms to 300 s	p= to =00	
Hold/Return Time	0 ms to 300 s		
Trigger Source	Internal, External or Manual		
Marker	Falling edge of Sync signal (programma	abla)	
Trigger Characteristics	Tailing edge of Sync signal (programma	ablej	
Trigger Input			
Level			
	TTL-compatible		
Slope	Rising or falling (selectable)		
Pulse Width	> 50 ns		
Latency	Sweep: <100 ns (typical)		
	Burst: <300 ns (typical)		
Trigger Output			
Level	TTL-compatible		
Pulse Width	> 60 ns (typical)		
Maximum Rate	1MHz		
Clock Reference			
Phase Offset			
Range	0° to 360°		
Resolution	0.001°		
External Reference Input	0.001		
	10 MHz ± 50 Hz		
Lock Range Level			
	80 mVpp to 10 Vpp		
Lock Time	< 2 s		
Internal Reference Output			
Frequency	10 MHz		
Level	632 mVpp (0 dBm), nominal value		
Sync Output			
Level	TTL-compatible		
Impedance	50 Ω, nominal value		
General Specifications			
Power			
Power Voltage	100-127 V, 45-440Hz		
	100-240 V, 45-65Hz		
Power Consumption	Less than 125 W		
Fuse	250V, T3A		
Display			
Туре	4.3-inch TFT LCD		
Resolution	480 Horizontal × RGB × 272 Vertical R	esolution	
Color	16 M color		
Environment	Operating: 10°C to 40°C		
Temperature Range	Operating: 10°C to 40°C		
	Non-Operating: -20°C to 60°C		
Cooling Method	Cooling by fans compulsively		
Humidity Range	Less than 35 ℃: ≤90% Relative Humidi		
	35 °C to 40 °C : ≤60% Relative Humidity	(RH)	
Altitude	Operating: Less than 3000 meters		
	Non-Operating: Less than 15000 meter	rs	
Mechanical			
	230 mm ×106 mm×501 mm		
Dimensions (W×H×D)			
Dimensions (W×H×D) Weight	with no package: 4.3 kg		
	with no package: 4.3 kg with package: 5.84 kg		
Weight	with package: 5.84 kg	J	
		١	

### Ordering Information

	Description	Order Number
Model	DG5352 (350 MHz, dual-channel)	DG5352
	DG5351 (350 MHz, single channel)	DG5351
	DG5252 (250 MHz, dual-channel)	DG5252
	DG5251 (250 MHz, single channel)	DG5251
	DG5102 (100 MHz, dual-channel)	DG5102
	DG5101 (100 MHz, single channel)	DG5101
Standard Accessories	Power Cord	
	USB Cable	CB-USB
	BNC Cable (1 meter)	CB-BNC-BNC-1
	Quick Guide (Hard Copy)	
	Resource CD (including User's Guide and Application Software)	
	Calibration Certificate	
Options	Frequency Hopping Module	DG5-FH
	Logic Signal Output Module	DG-POD-A
	Power Amplifier	PA1011
Optional Accessories	SMB(M) to SMB(M) Cable (1 meter)	CB-SMB(M)-SMB(M)-1
	SMB(M) to BNC(M) Cable (1 meter)	CB-SMB(M)-BNC(M)-1
	SMB(M) to BNC(F) Cable (1 meter)	CB-SMB(M)-BNC(F)-1
	40 dB Attenuator	ATT-40dB
	Rack Mount Kit	RMK-DG-5

RIGOL

www.rigol.com

For further information,please contact Rigol local Distributors