

# TRMS DIGITAL MULTIMETER 1000Vac/dc & BLUETOOTH

## DMM3500BT



- True RMS measurements
- LCD Display (6000 counts)
- AC/DC Voltage up to 1000 V
- AC/DC current up to 400mA
- Micro amperes Measurement
- Resistance, frequency, capacitance, temperature, diode test, continuity test.
- Non contact voltage detection (Adjustable sensitivity)
- High Frequency Rejection
- LoZ mode
- Autoranging
- Bargraphy display(60 segments)
- Datalogging (4000 registers)
- Bluetooth connectivity through *KPS Link APP*
- Built-in magnet sticker
- Safety rating: CAT IV 600V/CAT III 1000V



# DMM3500BT

## TRMS DIGITAL MULTIMETER 1000Vac/dc & BLUETOOTH

General	
Display	6000 counts
Auto power off	✓
Backlight	✓
Bargraph	✓
REL	✓
HOLD	✓
Diode and continuity test	✓
Auto-ranging	✓
Non Contact Voltage Detection	✓
LoZ mode	✓
High Frequency Rejection	✓
Dimensions	82x165x46mm
Weight	430g
Batteries	NEDA 15A/IEC LR6, 2*1,5V
Wireless Connectivity	Bluetooth
Data logging	4000 Registers
Standars	EC 61010-1, IEC/EN61010-2-033
Desing	Holster with probe holder, tilt stand and magnetic sticker
Safety rating	CAT IV 600V, CAT III 1000V
Accesories included	Standard test leads, thermocouple, batteries, user manual

# DMM3500BT

## TRMS DIGITAL MULTIMETER 1000Vac/dc & BLUETOOTH

Specs	
TRMS	✓
DC Voltage (mV)	600mV
DC Voltage (V)	1000V
AC Voltage (V)	1000V
Low Current (µAac/dc)	400mA
Frequency	100kHz
Resistance	40MΩ
Diode	1,5V
Continuity	✓
Capacitance	10mF
Temperature	-40°C ~ 400°C

Product Code Information	
SKU	KPSDMM3500BTCBINT
EAN code	8435394886381
UPC code	810053676899
Pcs/export carton	15